



#### Description

HBG-100 series is a 100W AC/DC LED driver featuring the circular shape design. It operates from 90~305VAC and offers the constant current output models with different rated voltage between 24V and 60V. Thanks to the high efficiency up to 91.5%, with the fanless design, the entire series is able to operate for -40°C ~ +85°C case temperature under free air convection. The design of metal housing and IP67/IP65 ingress protection level allows this series to fit both indoor and outdoor applications. HBG-100 is equipped with various function options, such as dimming methodologies, so as to provide the optimal design flexibility for LED lighting system.

#### Model Encoding



Туре	IP Level	Function	Note
Blank	IP67	lo fixed.	In Stock
A	IP65	lo adjustable through built-in potentiometer.	In Stock
В	IP67	3 in 1 dimming function (1~10Vdc, 10V PWM signal and resistance)	In Stock
AB	IP65	Io adjustable through built-in potentiometer with 3 in 1 dimming function	In Stock
DA	IP67	DALI control technology.	In Stock



### HBG-100 series

#### SPECIFICATION

	HBG-100-24							
DATED CUDDENT	4.4		HBG-100-36	HBG-100-48	HBG-100-60			
RATED CURRENT	4A		2.7A	2A	1.6A			
RATED POWER	96W		97.2W	96W	96W			
					36 ~ 60V			
OPEN CIRCUIT VOLTAGE(max.)				49V	62V			
CURRENT AD.I RANGE		B-Type (via b	, ,					
CONNENT ADD. NAMOL			1.62~2.7A	1.2 ~ 2A	1.0 ~ 1.6A			
CURRENT RIPPLE	5.0% max. @rated	d current						
CURRENT TOLERANCE	±5.0%							
SETUP TIME Note.4	2000ms / 115VAC 500ms / 230VAC							
VOLTAGE RANGE Note.3	90 ~ 305VAC 127 ~ 431VDC (Please refer to "STATIC CHARACTERISTIC" section)							
FREQUENCY RANGE	47~63Hz							
POWER FACTOR	PF>0.96/115VAC, PF>0.96/230VAC, PF>0.94/277VAC@full load (Please refer to "POWER FACTOR (PF) CHARACTERISTIC" section)							
TOTAL HARMONIC DISTORTION	THD< 20%(@load≧60%/115VC,230VAC; @load≧75%/277VAC) (Please refer to "TOTAL HARMONIC DISTORTION(THD)" section)							
EFFICIENCY (Tvp.) Note 5	90.5%		91%	91%	91.5%			
		0.54/230			01.070			
,								
,								
CIRCUIT BREAKER	4 units (circuit breaker of type B) / 8 units (circuit breaker of type C) at 230VAC							
LEAKAGE CURRENT								
OVER CURRENT								
		miting						
OVER VOLTAGE				54 ~ 63V	65 ~ 75V			
OVERVOEIAGE	Shut down o/p voltage re-power on to recovery							
OVER TEMPERATURE	Shut down o/p voltage re-power on to recovery							
WORKING TEMP.	Tcase=-40 ~ +85°(	C (Please ref	fer to " OUTPUT LOAD	vs TEMPERATURE" section)				
MAX. CASE TEMP.	Tcase=+85℃							
WORKING HUMIDITY	20 ~ 95% RH non-condensing							
STORAGE TEMP., HUMIDITY	-40 ~ +80°C , 10 ~ 95% RH							
TEMP. COEFFICIENT	±0.03%/°C (0~50°C)							
VIBRATION	10 ~ 500Hz, 5G 12min./1cycle, period for 72min. each along X, Y, Z axes							
SAFETY STANDARDS	UL8750(type"HL"), CSA C22.2 No.250.13-12, ENEC BS EN/EN61347-1,BS EN/EN61347-2-13 independent, BS EN/EN62384; GB19510.1, GB19510.14, BIS IS15885(for 36A,48A,60A only), EAC TP TC 004,IP65 or IP67 approved							
DALI STANDARDS	Compliance to IEC62386-101, 102, 207 for DA-Type only							
WITHSTAND VOLTAGE	I/P-O/P:3.75KVAC I/P-FG:2KVAC O/P-FG:0.5KVAC							
ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C/ 70% RH							
EMC EMISSION	Compliance to BS EN/EN55015, BS EN/EN61000-3-2 Class C (@load≧60%) ; BS EN/EN61000-3-3, GB17743 and GB17625.1, EAC TP TC 020							
EMC IMMUNITY	Compliance to BS EN/EN61000-4-2,3,4,5,6,8,11, BS EN/EN61547, light industry level (surge immunity:Line-Earth:4KV, Line-Line:2KV), EAC TP TC 020							
MTBF	2433.4K hrs min.	Telcordia S	SR-332 (Bellcore) ;299.	3K hrs min. MIL-HDBK-217	F (25°C)			
DIMENSION	$\phi$ 130mm *66.5mr	m (D * H)						
PACKING	1.18Kg; 12pcs/15.	7Kg/1.43CU	FT(Blank/A/B Type),1.8	9CUFT(E Type)				
<ol> <li>Be-rating may be needed under low input voltages. Please refer to "STATIC CHARACTERISTIC" sections for details.</li> <li>Length of set up time is measured at cold first start. Turning ON/OFF the driver may lead to increase of the set up time.</li> <li>The DA type power supply is less efficient than the typical efficiency in specification by 1%.</li> <li>The driver is considered as a component that will be operated in combination with final equipment. Since EMC performance will be affected by the complete installation, the final equipment manufacturers must re-qualify EMC Directive on the complete installation again.</li> <li>This series meets the typical life expectancy of &gt;50,000 hours of operation when Tcase, particularly (c) point (or TMP, per DLC), is about 75°C or less</li> </ol>								
	OPEN CIRCUIT VOLTAGE(max.)         CURRENT ADJ. RANGE         CURRENT RIPPLE         CURRENT TOLERANCE         SETUP TIME       Note.3         FREQUENCY RANGE         POWER FACTOR         TOTAL HARMONIC DISTORTION         EFFICIENCY (Typ.)       Note.5         AC CURRENT (Typ.)         INRUSH CURRENT (Typ.)         MAX. No. of PSUs on 16A         CIRCUIT BREAKER         LEAKAGE CURRENT         OVER VOLTAGE         OVER VOLTAGE         OVER VOLTAGE         OVER VOLTAGE         OVER TEMPERATURE         WORKING TEMP.         MAX. CASE TEMP.         WORKING HUMIDITY         STORAGE TEMP., HUMIDITY         TEMP. COEFFICIENT         VIBRATION         SAFETY STANDARDS         DALI STANDARDS         WITHSTAND VOLTAGE         ISOLATION RESISTANCE         EMC IMMUNITY         MTBF         DIMENSION         PACKING         1. All parameters NOT specia         2. Please refer to "DRIVING M         3. De-rating may be needed u         4. Length of set up time is me         5. The DA type power supply <t< td=""><td>CURRENT ADJ. RANGE         Adjustable for A/A           CURRENT RIPPLE         5.0% max.@rated           CURRENT TOLERANCE         ±5.0%           SETUP TIME         Note.4         2000ms / 115VAC           VOLTAGE RANGE         Note.3         90 ~ 305VAC           POWER FACTOR         PF&gt;0.96/115VAC, (Please refer to "C           POWER FACTOR         PF&gt;0.96/115VAC, (Please refer to "C           TOTAL HARMONIC DISTORTION         THD&lt;20%@loan (Please refer to "C           TOTAL HARMONIC DISTORTION         THD&lt;20%@loan (Please refer to "C           TRUSH CURRENT (Typ.)         1.1A / 115VAC           INRUSH CURRENT (Typ.)         COLD START 60/2           MAX. No. of PSUs on 16A CIRCUIT BREAKER         4 units (circuit breaction of the constant current ling)           OVER VOLTAGE         95 ~ 108%           OVER VOLTAGE         Shut down o/p vol           OVER VOLTAGE         Shut down o/p vol           WORKING TEMP.         Tcase=.40 ~ +85°C           WORKING TEMP.         Tcase=.40 ~ +85°C</td><td>OPEN CIRCUIT VOLTAGE(max.)         25∨           CURRENT ADJ. RANGE         Adjustable for A/AB-Type (via 1 2.4 ~ 4A           CURRENT RIPPLE         5.0% max.@rated current           CURRENT TOLERANCE         ±5.0%           SETUP TIME         Note.4         2000ms / 115VAC           VOLTAGE RANGE         Note.3         90 ~ 305VAC         127 ~ 431V (Please refer to "STATIC CHA           FREQUENCY RANGE         47 ~ 63Hz         PF&gt;0.96/115VAC, PF&gt;0.96/230 (Please refer to "TOTAL HARMONIC DISTORTION         THD &lt; 20%(@load≥60%/115V (Please refer to "TOTAL HARM           EFFICIENCY (Typ.)         Note.5         90.5%         AC CURRENT (Typ.)         1.1A / 115VAC         0.5A / 230           MAX. No. of PSUs on 16A CIRCUIT BREAKER         4 units (circuit breaker of type         1.1A / 115VAC         0.5A / 230           OVER CURRENT         40.75mA / 277VAC         95 ~ 108%         0         0VER voltage           OVER VOLTAGE         Shut down o/p voltage re-power         28 ~ 35V         0VER voltage re-power           MAX. CASE TEMP.         Tcase=+85°C         0         0VER NG TEMP.         10 ~ 500Hz, 56 12min./1cycle           SAFETY STANDARDS         Compliance to BC/2386-101,         WITHSTAND AVOLTAGE         I/P -0/P:3.75KVAC         I/P -61;           DALI STANDARDS         Compliance to BS EN/EN5010 (B17743 and GB17625.1,</td><td>OPEN CIRCUIT VOLTAGE(max.)         25V         37V           CURRENT ADJ. RANGE         Adjustable for A/AB-Type (via built-in potentiometer)         2.4 ~ 4A         1.62 ~ 2.7A           CURRENT RIPPLE         5.0% max. @rated current         1.62 ~ 2.7A         1.62 ~ 2.7A           CURRENT TOLERANCE         45.0%         90 ~ 305VAC         127 ~ 431VDC           VOLTAGE RANGE         Note.4         2000ms / 115VAC         500ms / 230VAC           POWER FACTOR         PF&gt;0.96/115VAC, PF&gt;0.96/230VAC, PF&gt;0.94/277VAC (Please refer to "POWER FACTOR (PF) CHARACTERS         PF&gt;0.96/115VAC, PF&gt;0.94/270VAC           POWER FACTOR         PF&gt;0.96/115VAC, PF&gt;0.94/270VAC         90 ~ 305VAC         1.1A / 15VAC           TOTAL HARMONIC DISTORTION         THD &lt; 20% (@load 260%/115VC, 230VAC</td>         0.45A / 277V/           INRUSH CURRENT (Typ.)         Note.5         90.5%         91%           AC CURRENT (Typ.)         COLD START 60A(twidth=550)µs measured at 50% lpc           MAX. No. of PSUs on 16A         4 units (circuit breaker of type B) / 8 units (circuit bre</t<>	CURRENT ADJ. RANGE         Adjustable for A/A           CURRENT RIPPLE         5.0% max.@rated           CURRENT TOLERANCE         ±5.0%           SETUP TIME         Note.4         2000ms / 115VAC           VOLTAGE RANGE         Note.3         90 ~ 305VAC           POWER FACTOR         PF>0.96/115VAC, (Please refer to "C           POWER FACTOR         PF>0.96/115VAC, (Please refer to "C           TOTAL HARMONIC DISTORTION         THD<20%@loan (Please refer to "C           TOTAL HARMONIC DISTORTION         THD<20%@loan (Please refer to "C           TRUSH CURRENT (Typ.)         1.1A / 115VAC           INRUSH CURRENT (Typ.)         COLD START 60/2           MAX. No. of PSUs on 16A CIRCUIT BREAKER         4 units (circuit breaction of the constant current ling)           OVER VOLTAGE         95 ~ 108%           OVER VOLTAGE         Shut down o/p vol           OVER VOLTAGE         Shut down o/p vol           WORKING TEMP.         Tcase=.40 ~ +85°C           WORKING TEMP.         Tcase=.40 ~ +85°C	OPEN CIRCUIT VOLTAGE(max.)         25∨           CURRENT ADJ. RANGE         Adjustable for A/AB-Type (via 1 2.4 ~ 4A           CURRENT RIPPLE         5.0% max.@rated current           CURRENT TOLERANCE         ±5.0%           SETUP TIME         Note.4         2000ms / 115VAC           VOLTAGE RANGE         Note.3         90 ~ 305VAC         127 ~ 431V (Please refer to "STATIC CHA           FREQUENCY RANGE         47 ~ 63Hz         PF>0.96/115VAC, PF>0.96/230 (Please refer to "TOTAL HARMONIC DISTORTION         THD < 20%(@load≥60%/115V (Please refer to "TOTAL HARM           EFFICIENCY (Typ.)         Note.5         90.5%         AC CURRENT (Typ.)         1.1A / 115VAC         0.5A / 230           MAX. No. of PSUs on 16A CIRCUIT BREAKER         4 units (circuit breaker of type         1.1A / 115VAC         0.5A / 230           OVER CURRENT         40.75mA / 277VAC         95 ~ 108%         0         0VER voltage           OVER VOLTAGE         Shut down o/p voltage re-power         28 ~ 35V         0VER voltage re-power           MAX. CASE TEMP.         Tcase=+85°C         0         0VER NG TEMP.         10 ~ 500Hz, 56 12min./1cycle           SAFETY STANDARDS         Compliance to BC/2386-101,         WITHSTAND AVOLTAGE         I/P -0/P:3.75KVAC         I/P -61;           DALI STANDARDS         Compliance to BS EN/EN5010 (B17743 and GB17625.1,	OPEN CIRCUIT VOLTAGE(max.)         25V         37V           CURRENT ADJ. RANGE         Adjustable for A/AB-Type (via built-in potentiometer)         2.4 ~ 4A         1.62 ~ 2.7A           CURRENT RIPPLE         5.0% max. @rated current         1.62 ~ 2.7A         1.62 ~ 2.7A           CURRENT TOLERANCE         45.0%         90 ~ 305VAC         127 ~ 431VDC           VOLTAGE RANGE         Note.4         2000ms / 115VAC         500ms / 230VAC           POWER FACTOR         PF>0.96/115VAC, PF>0.96/230VAC, PF>0.94/277VAC (Please refer to "POWER FACTOR (PF) CHARACTERS         PF>0.96/115VAC, PF>0.94/270VAC           POWER FACTOR         PF>0.96/115VAC, PF>0.94/270VAC         90 ~ 305VAC         1.1A / 15VAC           TOTAL HARMONIC DISTORTION         THD < 20% (@load 260%/115VC, 230VAC	OPEN CIRCUIT VOLTAGE(max.)         25V         37V         49V           CURRENT ADJ. RANGE         Adjustable for A/AB-Type (via bullit-in potentiometer)         1.2 ~ 2A           CURRENT RIPPLE         5.0% max. @rated ourrent         1.62 ~ 2.7A         1.2 ~ 2A           CURRENT RIPPLE         5.0% max. @rated ourrent         1.62 ~ 2.7A         1.2 ~ 2A           SETUP TIME         Note.3         90 ~ 305VAC         127 ~ 431VDC           VOLTAGE RANGE         Note.3         90 ~ 305VAC         127 ~ 431VDC           POWER FACTOR         PF-0.96/115VAC, PF-0.96/230VAC, PF-0.94/277VAC.@full load         PP-0.96/115VAC, PF-0.96/230VAC, Qload 257%/277VAC.0           POWER FACTOR         PF-0.96/115VAC, PF-0.96/230VAC, Qload 257%/277VAC.0         PH-0.96/115VAC, PF-0.96/230VAC, Qload 257%/277VAC.0           FEFICIENCY (Typ.)         Note.5         90.5%         91%         91%           AC CURRENT (Typ.)         1.14 / 115VAC         0.42 / 230VAC         0.45A / 277VAC           INUSUS CURRENT (Typ.)         1.14 / 115VAC         0.42 / 230VAC         0.45A / 270VAC           OVER CURRENT         40.015 Class read rol odu/width=550, measured at 50% (pask) at 230VAC, Class read rol odu/width=550, measured at 50% (pask) at 230VAC         230VAC           OVER VOLTAGE         25 - 108%         Constant current limiting         230VAC			



## HBG-100 series



 $\,$   $\!$   $\!$   $\!$  This series works in constant current mode to directly drive the LEDs.



Typical output current normalized by rated current (%)

In the constant current region, the highest voltage at the output of the driver depends on the configuration of the end systems.

Should there be any compatibility issues, please contact MEAN WELL.







# HBG-100 series

Note: In the case of turning the lighting fixture down to 0% brightness, please refer to the configuration as follow, or please contact MEAN WELL for other options.



Using a switch and relay can turn ON/OFF the lighting fixture.

**※ DALI Interface (primary side; for DA-Type)** 

- Apply DALI signal between DA+ and DA-.
- DALI protocol comprises 16 groups and 64 addresses.
- First step is fixed at 8% of output.







LIFE TIME



Tcase ( $^{\circ}\!C$  )







# HBG-100 series

※ AB-Type



• (c) : Max. Case Temperature.(case temperature measured point)

• Ta: Ambient Temperature measured point

#### ■ INSTALLATIONS

Hanger	Chain	Spot Light	High Bay Light	Stage Light

#### Caution

- · Please inspect the appearance of the driver if the package is damaged. There should not be any cracks.
- Please do not drop or bump the driver.
- All screws including the suspension screw should be paired with a spring washer and locked tight.
- The entire luminaire, including the driver, should be limited to 10Kg or less.
- The luminaire should be cautiously protected from damage due to shock throughout packaging and transportation.
- Please thoroughly follow the preceding cautionary notes to prevent the luminaire from falling, leading to injuries.